

APPROVED METER SOCKETS

(revised Jan. 2018)



SINGLE PHASE

200 AMP Service - Lever Bypass

Milbank	U4801 or equiv.	OH/UG	
---------	-----------------	-------	--

200 AMP Service - Socket/Main - Lever Bypass

Milbank	U5871 or equiv.	OH/UG	Preferred
Milbank	U5872 or equiv.	OH/UG	Preferred
Milbank	U4322-0-579 or equiv.	UG	Meter pedestal

200 AMP Service – 2-Position/Dual Socket - Lever Bypass

Milbank	U2872 or equiv.	OH/UG	Electrician must provide mechanical lugs (K1350) for line & load side
---------	-----------------	-------	---

320 AMP Service - Lever Bypass

Milbank	1797-RXL-K3-K2-1L or equiv.	OH only	Factory-installed lugs
Milbank	U2448 or equiv.	OH/UG	Electrician must provide mechanical lugs (K1350) for line & (K1350 or K1540) load side
Milbank	U1797-0-K3L-K2L or equiv.	UG only	Factory-installed lugs

400 AMP/800 AMP Service - CT meter package (6-terminal socket)

	Cooperative will provide meter sockets at member's expense.	OH/UG	Electrician must provide CT cabinet, mechanical lugs for line and load side of cabinet.
--	---	-------	---

THREE PHASE

200 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

Milbank	U9701-RXL or equiv.	OH only	Electrician must provide mechanical lugs
---------	---------------------	---------	--

320 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

Milbank	U4911-X-QG-BL or equiv.	OH/UG	Electrician must provide mechanical lugs
Milbank	U3000-0-K3L-K2L or equiv.	UG only	Factory-installed lugs

400 AMP or Larger - 3 PHASE - CT meter package

Meter socket will be provided by Cooperative (3 phase only).

Electrician must provide CT cabinet and mechanical lugs for line & load side of cabinet.